DATASHEET

Variable Speed Drives





Product coding : CFW500B06P5T4DB20C2H00

: 11998572

Product reference : CFW500 Accessory module (control) : Without plug-in

Power supply : 380-480 V Input minimum-maximum voltage : 323-528 V

- In : 3 - Out : 3

Supply voltage range	380-480 V		
Overload cicle	Normal Overload (ND)	Heavy Overload (HD)	
Rated current (HD)	6.5	6.5	
Overload current for 60 sec (HD)	10	10	
Overload current for 3 sec (HD)	10	10	

Maximum applicable motor:

Voltage/Frequency	Power (HP/kW) [1]		
voltage/i requericy	Normal Overload (ND)	Heavy Overload (HD)	
380V / 50Hz	Not applicable	3 / 2,2	
380V / 60Hz	Not applicable	3 / 2,2	
400V / 50Hz	Not applicable	4/3	
400V / 60Hz	Not applicable	3 / 2,2	
440V / 50Hz	Not applicable	4/3	
440V / 60Hz	Not applicable	ole 4/3	
460V / 60Hz	Not applicable		
480V / 60Hz	Not applicable		

Accessory module (control) : Without plug-in
Dynamic braking [2] : Standard with braking
External electronic suply 24Vcc : Not available

External electronic suply 24Vcc : Not available Safety Stop : Not available

Internal RFI filter : With filter (C2 category)

: Not available
Link Inductor : No
Memory card : Not included in the product

USB port : Only with plug-in Line frequency : 50/60Hz Line frequency range (minimum - maximum) : 48-62 Hz

Phase unbalance : Less or equal to 3% of input rated line voltage

Transient voltage and overvoltage : Category III Single-phase input current [3] : Not applicable

Single-phase input current [3] : Not applical Three-phase input current [3] : 7,9 A

Power factor : 0,75

Displacement factor : 0,98

Rated efficiency : \geq 97%

Maximum connections (power up cycles - on/off) per hour : 10 (1 each 6 minutes)

DC power supply : Allow Standard switching frequency : 5 kHz

Standard switching frequency : 5 kHz
Selectable switching frequency : 2,5 and 15 kHz
Real-time clock : Not available
COPY Function : Yes, by MMF

Dissipated power:

Mounting type	Overload		
3 37	ND	HD	
Surface	105 W	105 W	
Flange	Not applicable	Not applicable	

Source available to the user

Output voltage : 24 Vcc Maximum capacity : 150 mA

Power supply
Control method
: Switched-mode power supply
: V/f, VVW, Sensorless and Encoder

Encoder interface : Only with plug-in
Control output frequency : 0-500 Hz
Frequency resolution : 0,015 Hz
- Speed resolution : 1% of rated speed

- Speed range : 1:20

24/09/2020	The information contained are reference values. Subject	1 / 1
	to change without notice. Image merely illustrative.	1/4

DATASHEET

Variable Speed Drives



- Speed resolution : 1% of rated speed

- Speed range : 1:30

- Speed resolution : 0,5% of rated speed

- Speed range : 1:100

- Speed resolution : 0,1% of nominal speed

- Speed range : Up to 0 rpm

Quantity (standard) : Only with plug-in Levels : Not applicable Impedance for voltage input : Not applicable Impedance for current input : Not applicable Function : Not applicable Maximum allowed voltage : Not applicable

Quantity (standard) : Only with plug-in Activation : Not applicable Maximum low level : Not applicable Minimum high level : Not applicable Input current : Not applicable Maximum input current : Not applicable Function : Not applicable

Analog outputs

Maximum allowed voltage

Analogic outputs - Quantity (standard) : Only with plug-in Levels : Not applicable RL for voltage output : Not applicable

RL for current output : Not applicable
Function : Not applicable

Not applicable

Not applicable

Digital outputs

Digital outputs - Quantity (standard) : 3 NO relay and 1 transistor

: Not applicable

Maximum voltage: Not applicableMaximum current: Not applicableFunction: Not applicable

Available protection

- Output phase-phase overcurrente/Short

- Overcurrent/Short circuit phase-ground

- Under/Overvoltage in power

- Heat sink overtemperature

- Motor overload

- IGBT's modules overload

- Fault/External alarm

- Programming error

Operation interface (HMI)

Avaliability : Included in the product

Installation : Fixed HMI

Number of HMI buttons : 9

Display : Numeric LCD Indication accuracy : 5% of rated current

Speed resolution : 0,1 Hz Standard HMI degree of protection : IP20

HMI battery type : Not applicable
HMI battery life expectancy : Not applicable
Remote HMI type : Accessory
Remote HMI frame : Not applicable

Remote HMI degree of protection : IP54

Enclosure : IP20
Degree of pollution : 2

RoHS : Yes Conformal Coating : 3C2 - Size : B

DATASHEET

Variable Speed Drives



- Height : 199 mm / 7.8 in - Width : 100 mm / 3.9 in - Depth : 160 mm / 6.3 in - Weight : 1,2 kg / 2.6 lb

Mechanical Installation

Mounting position : Surface or DIN rail

Fixing screw : M4

Tightening torque : 2 N.m / 1.48 lb.ft

Allows side-by-side assembly : Yes, maximum ambient temperature 40°C

Minimum spacing around the inverter:

- Top : 35 mm / 1.38 in - Bottom : 50 mm / 1.97 in - Front : 40 mm / 1.57 in - Side : 15 mm / 0.59 in

Cable gauges and tightening torques:

	Recommended cable gauge	Recommended tightening torque	
Power	1,5 mm² (16 AWG)	0,5 N.m / 0,37 lb.ft	
Braking	2,5 mm² (14 AWG)	0,5 N.m / 0,37 lb.ft	
Grounding	2,5 mm² (14 AWG)	0,5 N.m / 0.37 lb.ft	
Control	0,5 to 1,5 mm ² (20 to 14 AWG)	0,5 N.m / 0.37 lb.ft	

SoftPLC : Yes, incorporated

Standards

Safety	- UL 508C - Power conversion equipment.
	- UL 840 - Insulation coordination including clearances and creepage distances
	for electrical equipment.
	- EN 61800-5-1 - Safety requirements electrical, thermal and energy.
	- EN 50178 - Electronic equipment for use in power installations.
	- EN 60204-1-Safety of machinery. Electrical equipment of machines. Part
	1: General requirements. Note: To have a machine in accordance with that
	standard, the manufacturer of the machine is responsible for the installation of
	an emergency-stop device and a network switching equipment.
	- EN 60146 (IEC 146) - Semiconductor converters.
	- EN 61800-2 - Adjustable speed electrical power drive systems - Part 2:
	General requirements - Rating specifications for low voltage adjustable
	frequency AC power drive systems.
Electromagnetic Compatibility	- EN 61800-3 - Adjustable speed electrical power drive systems - Part 3: EMC
	product standard including specific test methods.
	- EN 55011 - Limits and methods of measurement of radio disturbance
	characteristics of industrial, scientific and medical (ISM) radio-frequency
	equipment.
	- CISPR 11 - Industrial, scientific and medical (ISM) radio-frequency equipment
	- Electromagnetic disturbance characteristics - Limits and methods of
	measurement.
	- EN 61000-4-2 - Electromagnetic compatibility (EMC) - Part 4: Testing and
	measurement techniques - Section 2: Electrostatic discharge immunity test.
	- EN 61000-4-3 - Electromagnetic compatibility (EMC) - Part 4: Testing
	and measurement techniques - Section 3: Radiated, radio-frequency,
	electromagnetic field immunity test.
	- EN 61000-4-4 - Electromagnetic compatibility (EMC) - Part 4: Testing and
	measurement techniques - Section 4: Electrical fast transient/burst immunity
	test.
	- EN 61000-4-5 - Electromagnetic compatibility (EMC) - Part 4: Testing and
	measurement techniques - Section 5: Surge immunity test.
	- EN 61000-4-6 - Electromagnetic compatibility (EMC)- Part 4: Testing and
	measurement techniques - Section 6: Immunity to conducted disturbances,
	induced by radio-frequency fields.
Mechanical Construction	- EN 60529 e UL 50

Notes

- 1) Motor power is orientative, valid for standard WEG Motors of IV poles. The correct sizing must be done according to the nominal current of the motor used, which must be less than or equal to the rated output current of the inverter;
- 2) Braking resistor is not included;
- 3) Considering minimum line impedance of 1%;
- 4) For more information, refer to the user manual of CFW500;

24/09/2020	The information contained are reference values. Subject
24/09/2020	to change without notice. Image merely illustrative.

DATASHEET Variable Speed Drives



•		
5) All images are merely illust 6) For operation with switching	rative. g frequency above nominal, apply derating to the output current (refer to the user man	ual).
24/09/2020	The information contained are reference values. Subject	4 / 4

